
Yucel-Series - Valve Regulated Lead Acid Battery Y2.1-12

Data Sheet

SPECIFICATIONS		
Nominal voltage	12	V
20-hr rate Capacity to 1.75VPC at 20°C	2.1	Ah
10-hr rate Capacity to 1.75VPC at 20°C	1.95	Ah
DIMENSIONS		
Length	178 (±1)	mm
Width	35 (±1)	mm
Height	60 (±1)	mm
(height over terminals)	66 (±2)	mm
Mass (typical)	1	kg
TERMINAL TYPE		
FASTON (Quickfit / release)	4.75	mm
OPERATING TEMPERATURE RANGE		
Storage	-20°C to +60°C	
Charge	-15°C to +50°C	
Discharge	-20°C to +60°C	
STORAGE		
Capacity loss per month at 20°C (approx)	3	%
CASE MATERIAL		
Standard Option	ABS (UL.94:HB)	
Flame retardant option (FR)	ABS (UL94:V0)	
CHARGE VOLTAGE		
Float charge voltage at 20°C	13.65 (±1%)	V
l loat charge voltage at 20 C	2.275 (±1%)	V/cell
Float Charge voltage temperature correction factor (for variations from the standard 20°C)	-3	mV/cell/°C
Cyclic (or Boost) charge at 20°C	14.5 (±3%) 2.42 (±3%)	V V/cell
Cyclic Charge voltage temperature correction factor (for variations from the standard 20°C)	-4	mV/cell/°C
CHARGE CURRENT		
Float charge current limit	No limit	A
Cyclic (or Boost) charge current limit	0.525	A
MAXIMUM DISCHARGE CURRENT		
1 minute	21	A
SHORT-CIRCUIT CURRENT & INTERNAL RESISTANCE		
(according to EN IEC 60896-21)		
Internal resistance		l l
Ob ant Olyanit annuant	N/A	ml
Short-Circuit current	N/A N/A	mll A
IMPEDANCE		
IMPEDANCE	N/A	A
IMPEDANCE Measured at 1 kHz	N/A	A
IMPEDANCE Measured at 1 kHz PERFORMANCE & CHARACTERISTICS	N/A 90	A
IMPEDANCE Measured at 1 kHz PERFORMANCE & CHARACTERISTICS Refer to the technical manual	N/A 90	A
IMPEDANCE Measured at 1 kHz PERFORMANCE & CHARACTERISTICS Refer to the technical manual DESIGN LIFE	N/A 90 YUCEL	A mil





3RD PARTY CERTIFICATIONS

ISO 9001 - Quality Management Systems
ISO 14001 - Environmental Management Systems
EN 18001 - OHSAS Management Systems
UNDERWRITERS LABORATORIES Inc.



STANDARDS

IEC61056







ALL DATA IS SUBJECT TO CHANGE WITHOUT NOTICE Issue No.: V.1 / Issue Date: July 2010



YUASA BATTERY SALES UK LTD. Unit 22 Rassau Industrial Estate Ebbw Vale, Gwent NP23 5SD UK

Installation

Can be installed and operated in any orientation except permanently inverted

nandies

Batteries must not be suspended by their handles (where fitted)

Vent valves

Each cell is fitted with a low pressure release valve to allow gasses to escape and then reseal.

Gas Release

VRLA Batteries release hydrogen gas which can form explosive mixtures in air. Do not place inside a sealed container

Recycling

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations