



# Data Sheet UTP1300 Series DC Power Supply

| M1 OVP                      |
|-----------------------------|
| M2 OCP CURRENT<br>M3 ON/OFF |
| + 32V/10A - GND             |

# Main Features

- •Rated output voltage: 0 ~ 32V
- •Rated output current: 0 ~ 6 / 10A
- •Setting resolution: 10mV / 1mA
- •4-digit voltage / current high precision display
- •Minimum overall dimension
- •Overvoltage and overcurrent protection
- •Keyboard lock
- •Three groups of preset
- Independent output switch
- •Encoder knob

# DC Power Supply Panel





①Voltage display ②Current display ③ "Ml~M3" storage/recall buttons ④OVP setting button
⑤OCP setting button ⑥Output on/off button ⑦Voltage output adjustment knob
⑧Current adjustment knob ⑨Positive (red) output terminal ⑩Negative (black) output terminal
⑪Ground terminal ⑫Power supply switch ⑬Cooling fan ⑭AC selector
⑮ Power supply input socket ⑯Fuse holder

### Product Introduction

UTP1310 high-quality economical DC power supply has 4 digits voltage and current display, settable over voltage protection (OVP) and over current protection (OCP). It is an ideal tool for school, product line, appliance maintenance center, etc. with highly stable performance.

#### Rated output

UTP1300 series is a high-efficiency DC power supply with maximum output voltage of 32V, maximum current of 10A and maximum output power of 320W. 4digits display, resolution 10mV / 1mA, the accuracy can meet the basic applications such as school, industry, R & D and manufacturing.



#### **Protection function**

After enabling the protection function, when the output reaches the protection value, an alarm will be triggered, and the output will be closed to protect the equipment. The instrument is equipped with a fan to adjust the temperature, so as to avoid excessive temperature of the equipment.



#### Save three sets of settings

UTP1300 series provides M1, M2 and M3 preset settings. The voltage and current group can be preset to avoid repeated setting time. Improve setup efficiency.



#### Keyboard locking

This series of power supplies provides keyboard locking. When this function is activated, the keyboard will be locked. It can avoid misoperation of the ongoing measurements.



# Technical Specification

| Model                |           | UTP1306                        | UTP3310                        |
|----------------------|-----------|--------------------------------|--------------------------------|
| Channel              | Channel   | 1                              | 1                              |
| Output Rating        | Voltage   | 0-32V                          | 0-32V                          |
|                      | Current   | 0~6A                           | 0~10A                          |
|                      | Power     | 192W                           | 320W                           |
| Load Regulation      | Voltage   | <0.1%+5mV                      | <0.1%+5mV                      |
|                      | Current   | <0.2%+3mA                      | <0.2%+3mA                      |
| Line Regulation      | Voltage   | <0.01%+5mV                     | <0.01%+5mV                     |
|                      | Current   | <0.2%+3mA                      | <0.2%+3mA                      |
| Programming Accuracy | Voltage   | <0.1%+1 digists                | <0.1%+1 digists                |
|                      | Current   | <0.2%+3mA                      | < 0.2%+3 digits                |
| Ripple               | Voltage   | 10mVrms                        | 10mVrms                        |
|                      | Current   | 5mArms                         | 5mArms                         |
| OVP                  | OVP       | 0~32V±0.2%FS                   | 0~32V±0.2%FS                   |
| OCP                  | 0CP       | 0~6.•A±0.2%FS                  | 0~10.0A±0.2%FS                 |
| Max                  | Voltage   | 32V±0.2%                       | 32V±0.2%                       |
|                      | Current   | 6.0A±0.2%                      | 10.0A±0.2%                     |
| Set resolution       | Voltage   | 10mV                           | 10mV                           |
|                      | Current   | 1mA                            | 1mA                            |
| Readback resolution  | Voltage   | 10mV                           | 10mV                           |
|                      | Current   | 1mA                            | 1mA                            |
| Display              | Display   | LED, 4-digit display           | LED, 4-digit display           |
| Dimension            | W*H*D     | 80*150*230 (mm)                | 80*150*230 (mm)                |
| Weight               | Net       | 1.9kg                          | 1.9kg                          |
| Input                | Voltage   | AC:110(±10%)V/220(±10%)V, 50Hz | AC:110(±10%)V/220(±10%)V, 50Hz |
| Environment          | Operating | 0C~40C,≤80%RH                  | 0°C~40°C,≤80%RH                |
|                      | Storage   |                                | -20 C~60 C, ≤80 % RH           |

Standard accessories

Alligator clip test lead double parallel

Power cable

### Warranty

Three-years warranty, excluding probes and accessories. Please visit https://instruments.uni-trend.com/list\_190/65.html to learn more information. To protect your investment, please purchase from UNI-T official authorized global distriburots.

# Find a Distributor

Find an authorized distributor here: https://instruments.uni-trend.com/Network

## Contact UNI-T

E-mail: info@uni-trend.com Test & Measurement Instruments Website: instruments.uni-trend.com UNI-T Corporate Website: www.uni-trend.com

UNI-T group maintains a wide products category includes Digital Test & Measurement instruments, Field Testing Meter, Infrared thermal imaging products. As early as 2008, we continue to introduce self-developed Digital Test and Measurement instruments to the market and have made remarkable achievements. At present, we have formed a variety of product lines of Oscilloscope, AWG, Spectrum Analyzer, Bench Multi-meter, Power Supply, DC Load, Power Meter, LCR Meter, Micro Ohm Meter and Data logger. We have separated instruments sub-sites, instruments.uni-trend.com, on the basis of the original website www.uni-trend.com, in order to be more targeted to provide customers with better service and value.

> UNI-TMKT/TMI/SCAL-2112-023 Instrument.uni-trend.com

