

ESD Workstation Kit

Descripiton

A comprehensive, easy to install basic ESD Safe workstation kit. The Kit has workspace or environment needed to build a static controlled workscape or environment items such as laptops, tablets, PCB's, Computer parts, Medical equipment and audio devices.

Kit Includes

- · 1x ESD Matting (600x1200mm) with 10mm stud in each corner
- · 1x ESD Protected Area vinyl sign
- · 1x Earth Bonding Plug 3x10mm Stud
- 1x10mm Fabric Adjustable Wrist Strap hypo allergenic
- · 1x10mm Coiled Earth Lead
- · 1x10mm Straight Lead
- · 1x Instruction Leaflet

Features

- · Reflection breaking surface to reduce glare and improve operator comfort
- · Prevention of sliding of delicate components thanks to excellent friction coefficient
- · Heat resistance: does not melt or burn coming into contact with hot metal parts or soldering debris
- · Suitable for loose laying: does not require application with adhesive
- · Good resistance to scratches and excellent flexibility and comfort

Notes

See our range of static gloves for components and devices that are susceptible to surface damage.

Test Method	Result
Material	Static dissipative
Thickness	2mm
Surface	Non-shining
Tester	ETS 406C Static Decay Meter, 3M Model 701 Test Kit for Static Control Surfaces
Hardness (ISO 7619)	75±5 shore A
Abrasion Resistance (ISO 4649, method A)	≤200mm³
Indentation (EN433)	≤0,20mm
Cigarette Burning Resistance (EN1399)	No burn
Chemical Resistance (EN423)	Resistant to chemical agents normally used for maintenance
Dimensional Stability (EN424 - 6h/80°C)	≤0.4%
Surface Resistance Top Layer (EN 100015.1-IEC61340)	About 10 ⁸ Ω
Surface Resistance Bottom Layer (EN 100015.1-IEC61340)	About 10 ⁵ Ω

Important Notice: This data sheet and its contents (the "Information") belong to Antistat or are licensed to it. No licence is granted for the use of it other than for $information\ purposes\ in\ connection\ with\ the\ products\ to\ which\ it\ relates.\ No\ licence\ of\ any\ intellectual\ property\ rights\ is\ granted.\ The\ Information\ is\ subject\ to\ change$ without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but Antistat assumes no responsibility for its accuracy of the contract of the contractor completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the same of theproducts for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the account of the purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the purpose and the $Information or use of it (including liability resulting from negligence or where Antistat was aware of the possibility of such loss or damage arising) is excluded. \\ @ Antistat was aware of the possibility of such loss or damage arising) is excluded. \\ @ Antistat was aware of the possibility of such loss or damage arising) is excluded. \\ @ Antistat was aware of the possibility of such loss or damage arising) is excluded. \\ @ Antistat was aware of the possibility of such loss or damage arising) is excluded. \\ @ Antistat was aware of the possibility of such loss or damage arising) is excluded. \\ @ Antistat was aware of the possibility of such loss or damage arising) is excluded. \\ @ Antistat was aware of the possibility of such loss or damage arising) is excluded. \\ @ Antistat was aware of the possibility of such loss or damage arising are the possibility of such loss or damage arising are the possibility of such loss or damage arising are the possibility of such loss or damage arising are the possibility of such loss or damage are the possi$









ESD Workstation Kit contents

ESD Protected Area Sign

- · Antistatic coating
- · Self adhesive: 0.4mm thick PVC
- · 300 x 150mm

Earth Bonding Plug 3x10mm Stud

- \cdot Incorporates a 3x10mm male stud for connection grounding wire
- · Designed to fit UK standard mains plug outlets
- · Neutral and mains voltage pins are plastic, earth pin is metal

Coiled Earth Lead

- Excellent quality for use with any kind of wrist band
- · Strong connection between the cord and 10mm stud
- · 10mm Stud / Banana Socket
- · Special conductive wire, outer covered with non-conductive PU
- · Diameter of cord: 2.4 mm / Diameter of coil cord: 1.02 cm
- Resistivity: 1M Ohm +/- 10%

Straight Earth Lead

- Excellent quality for use with any kind of Field Service Kit or Table Mat
- · Strong connection between the cord and stud
- · Outer covered with non-conductive PU
- · Length: 12ft
- Diameter of cord: 2.4 mmResistivity: 1M Ohm +/- 10%

Fabric Adjustable Wrist Strap Hypo Allergenic

- Sky blue band
- Adjustable for any size of wrist
- 10mm stud

069-0021

- ${\bf \cdot} \ {\bf High\ quality\ conductive\ interior,\ made\ of\ stainless\ steel\ nylon\ filament}$
- Outer side non-conductive nylon yarn
- $\boldsymbol{\cdot}$ Conductive back plate covers the metal part to prevent allergic reaction

Resistance from Band <10⁵ Ohms
Underside of Band <10⁴ Ohms
Test Method EN 61340-5-1
Top Side of Band < 10⁶ Ohms
Test Method EN 61340-5-1

ım Blue
ım Blue
ım Blue
m Blue
m Blue
m Blue

Important Notice: This data sheet and its contents (the "Information") belong to Antistat or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but Antistat assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where Antistat was aware of the possibility of such loss or damage arising) is excluded. @ Antistat.

ESD Workstation Kit with European Plug - Spanish









WWW.ANTISTAT.CO.UK