268 HANDHELD CASES

292 UNIVERSAL ENCLOSURES

318


342

Hex-Box IoT enclosure

Product overview

This UK manufactured Hex-Box has been designed with customisation and user flexibility at heart. The 100% recyclable housing features six self-retaining panels which you can mix and match to suit your requirement. The enclosure offers huge connector access and air flow benefits, ideal for industrial IoT settings. The design features and modern aesthetic create the perfect enclosure for walls (when paired with the wall mount bracket) or desktops (when paired with the rubber feet), each sold separately.

Key features



RANGE SPECIFICATION				
STANDARD UNIT INCLUDES	Base, top, 6 x panels, 3 x 16mm thread forming (Pozi CSK) screws			
	Base		UL94-V0 ABS	
MATERIALS	Тор		UL94-V0 ABS	
	Screws		BZP (Bright Zinc Plated Steel)	
	Grey		RAL7047	
COLOURS	Black		RAL9005	
	White		RAL9003	
COMPLIANCE	RoHS compliant			
OPERATING TEMPERATURE	-10°C to +80°C			
TEST RESULTS	Standard	Test	Result	Test report
	EN 62262	Impact test	IK07	TR112
	BS EN 60529	IP code	Vented: IP30	TR110
			Solid: IP40	TRIIO
SCREW TORQUE	Pozi CSK screws		0.3Nm	
	Country of origin		Great Britain (GB)	
PURCHASING INFORMATION	Commodity code		3923101000	
	Weight		120g	
	Enclosure type		Versatile sensor and IoT enclosures	
OPTIONS	For alternative colours and materials MOQs will apply			

Potential industries / applications

Industrial IoT, smart home, smart office, retail, speaker/ alarm buzzer, meeting room device, network equipment, environmental sensor equipment, development board electronics.



PCB mounting in the top and base

Six bosses in the top, four in the base with Raspberry Pi mountable footprint

Number index in base

Aids wall mounting

Self-retaining removable end panels

Allows cable entries from all sides. Panels can be easily customised and are available as either solid or vented

Guide for cable knock-out

Aids customisation with alignment of wall mount bracket

Smooth bevelled lid with flat top

Suitable for a 2.5" screen and perfect for digital printing




PCB positions

PCB MOUNTING POSITION	MAXIMUM PCB DIMENSION	
BASE	122.2mm Hex A/F	
ТОР	121.8mm Hex A/F	
When using a 1.6mm thick PCB, you will need No.4x6.5mm self-tapping screws		

Maximum PCB dimension

Enclosure dimensions

EXTERNAL (LxWxH)	INTERNAL (LxWxH)	WALL THICKNESS
146 x 130 x 45 mm	122.5 x 125.5 x 34.5 mm	2.5 mm





318

CHOOSE YOUR ENCLOSURE COMBINATION OPTION DESCRIPTION GREY (GY) BLACK (BK) WHITE (WH) 1 x enclosure and 6 x solid panels CBHEX1-60-GY CBHEX1-60-BK CBHEX1-60-WH 1 x enclosure, 5 x solid panels and 1 x vented panel CBHEX1-51-GY CBHEX1-51-BK CBHEX1-51-WH 1 x enclosure, 4 x solid panels and 2 x vented panels CBHEX1-42-GY CBHEX1-42-BK CBHEX1-42-WH 1 x enclosure, 3 x solid panels and 3 x vented panels CBHEX1-33-GY CBHEX1-33-BK CBHEX1-33-WH 1 x enclosure, 2 x solid panels and 4 x vented panels CRHEX1-24-GY CBHEX1-24-BK CBHEX1-24-WH CBHEX1-15-BK CBHEX1-15-WH 1 x enclosure, 1 x solid panels and 5 x vented panels CBHEX1-15-GY CBHEX1-06-GY CBHEX1-06-BK CBHEX1-06-WH 1 x enclosure and 6 x vented panels $1\,x$ enclosure, $2\,x$ customised solid panels to accommodate Raspberry Pi4, $2\,x$ solid panels and $3\,x$ vented panels CBHEX1-PI4-GY CBHEX1-PI4-BK CBHEX1-PI4-WH

Desk mount accessory

Product overview

The six rubber feet (CBHEX-FEET) turn your Hex-Box IoT Enclosure into a tabletop enclosure. Simply push the feet into the holes in the base of the Hex-Box IoT Enclosure.












Wall mount accessory

Product overview

Transform your Hex-Box IoT Enclosure into a wall mountable enclosure with the Circular Wall Mount Bracket. This revolutionary circular mounting bracket is packed full of mounting options and offers seamless and discrete mounting to retain the modern aesthetic look of your housing, whilst gaining additional functionality.

Key features



CIRCULAR WALL MOUNT BRACKET					
GREY (GY)	BLACK (BK)	WHITE (WH)	INCLUDED		
CBWMC-GY	CBWMC-BK	CBWMC-WH	1 x circular wall mount bracket, 3 x screws, 3 x lugs		

RANGE SPECIFICATION				
MATERIAL	Wall mount bracket	UL94-V0 ABS		
	Wall mount lugs	UL94-V0 ABS		
	Screws	BZP (Bright Zinc Plated Steel)		
DIAMETER	98.3 mm			
PURCHASING INFORMATION	Country of origin	Great Britain (GB)		
	Commodity code	3923101000		
	Weight	23.6g		

Rubber feet



Circular Wall Mount Bracket



2 x keyhole mounting slots

Allow for quick and easy wall mounting

Raised rib stand-offs

Help with stability of the enclosure on uneven walls

2 x sets of UK single gang back box mounting points In two off centre orientations

25mm cable entry knock-out for cable management

Customisation required to the enclosure base, using the guide provided $% \left(1\right) =\left(1\right) \left(1\right) \left($

Easy installation

Screw the lugs to the enclosure, twist 30 degrees and your bracket is attached

4 x static mount points/slots

Provides easy and flexible wall mount fitting

