Yucel-Series - Valve Regulated Lead Acid Battery

Y1.2-12N

The N designation is not printed on the battery it is an internal code

The N designation is not printed on the battery it is	s an internal code		
SPECIFICATIONS	10	.,	
Nominal voltage	12	V	
20-hr rate Capacity to 1.75VPC at 20°C	1.2	Ah	
10-hr rate Capacity to 1.75VPC at 20°C	1.11	Ah	
DIMENSIONS			
Length	97 (±1)	mm	
Width	43 (±1)	mm	
Height	52 (±1)	mm	
(height over terminals)	58 (±2)	mm	
Mass (typical)	0.57	kg	
TERMINAL TYPE			
FASTON (Quickfit / release)	4.75	mm	
OPERATING TEMPERATURE RANGE			
Storage	-20°C to	-20°C to +60°C	
Charge	-15°C to	-15°C to +50°C	
Discharge	-20°C to	-20°C to +60°C	
STORAGE			
Capacity loss per month at 20°C (approx)	3	%	
CASE MATERIAL			
Standard Option	ABS (UI	ABS (UL.94:HB)	
Flame retardant option (FR)	ABS (U	ABS (UL94:V0)	
CHARGE VOLTAGE	_		
Float charge voltage at 20°C	13.65 (±1%)	V	
1 loat charge voltage at 20 C	2.275 (±1%)	V/cell	
Float Charge voltage temperature correction factor (for variations from the standard 20°C)	-3	mV/cell/°C	
Cyclic (or Boost) charge at 20°C	14.5 (±3%)	V	
, , , , , , , , , , , , , , , , , , ,	2.42 (±3%)	V/cell	
Cyclic Charge voltage temperature correction factor (for variations from the standard 20°C)	-4	mV/cell/°C	
CHARGE CURRENT			
Float charge current limit	No limit	Α	
Cyclic (or Boost) charge current limit	0.3	Α	
MAXIMUM DISCHARGE CURRENT			
1 minute	12	Α	
SHORT-CIRCUIT CURRENT & INTERNAL RESISTANCE			
(according to EN IEC 60896-21)			
Internal resistance	N/A	m	
Short-Circuit current	N/A	Α	
IMPEDANCE			
Measured at 1 kHz	90	m	
PERFORMANCE & CHARACTERISTICS			
Refer to the technical manual	YUCEL		
DESIGN LIFE			
EUROBAT Classification: Standard Commercial	3 to 5	years	
Yuasa design life @ 20°C	up to 5	years	
SAFETY	up 10 0	years	

SAFETY

Installation

Can be installed and operated in any orientation except permanently inverted

Handles

Batteries must not be suspended by their handles (where fitted)

Vent valves

Each cell is fitted with a low pressure release valve to allow gasses to escape and then reseal.

Gas Release


VRLA Batteries release hydrogen gas which can form explosive mixtures in air. Do not place inside a sealed container

Recycling

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations

Data Sheet





3RD PARTY CERTIFICATIONS

ISO 9001 - Quality Management Systems
ISO 14001 - Environmental Management Systems
EN 18001 - OHSAS Management Systems
UNDERWRITERS LABORATORIES Inc.



STANDARDS

IEC61056







ALL DATA IS SUBJECT TO CHANGE WITHOUT NOTICE Issue No.: V.1 / Issue Date: August 2015



YUASA BATTERY SALES UK LTD. Unit 13, Hunts Rise South Marston Industrial Estate Swindon SN3 4TG